



## Mississippi Stair Light Installation Instructions

Fixture Color: ● ○ ●

LED Color: ○ ●

### Materials Needed:

- Power Drill with 7/16" drill bit
- Phillips Head Screwdriver
- Hammer

**Note:** It is assumed you have installed the power supply using its provided instructions.



1

Turn the system on (if you have a photo-eye system, unplug the photo eye micro-connector from the power supply so power is provided to the lights).

2

Connect the power supply to the first T-cable by plugging together the black landscape connectors.

3

Drill a 7/16" hole in the riser where you want the light mounted. Connect the light fixture through the hole to the micro-connector on the T-Cable.

Continued on back...

- ④ For each additional stair light, add another T-cable by attaching the landscape plugs and repeat step 3 to install the stair light.
- ⑤ Verify all lights are working and fasten each one to the stair riser with the supplied screws.
- ⑥ Use the wire staples to attach the wiring to the underside of the stairs.
- ⑦ If you have a photo-eye system, reconnect the photo eye when installation is complete.

**\*\*\*To ensure a water tight seal, push connectors firmly together.\*\*\***

**For additional product or installation assistance  
please call 302-294-6261.**

FOR USE WITH LANDSCAPE LIGHTING SYSTEM ONLY. THIS DEVICE IS ACCEPTED AS A LANDSCAPE LIGHTING SYSTEM WHERE THE SUITABILITY OF THE COMBINATION SHALL BE DETERMINED BY CSA OR LOCAL INSPECTION AUTHORITIES HAVING JURISDICTION. LANDSCAPE LIGHTING SYSTEMS ARE FOR OUTDOOR USE ONLY. NOT FOR USE IN DWELLING UNITS. DO NOT MOUNT POWER SUPPLY OR LUMINAIRES WITHIN 3M OF A SWIMMING POOL OR SPA. NOT FOR USE WITH SUBMERSIBLE FIXTURES. USE ONLY WITH I-LIGHTING EASY PLUG CONNECTOR CABLES AND POWER SUPPLIES. FOR ADDITIONAL CABLES PLEASE CALL 888-305-4232. THE POST LIGHTS PULL 0.7 MILLI AMPS EACH. USE ONLY 90% OF THE POWER SUPPLIES WATTAGE, ALLOWING 10% FREE. LOW VOLTAGE CABLE SHALL: BE PROTECTED BY ROUTING IN CLOSE PROXIMITY TO THE LUMINAIRE OR FITTING, OR NEXT TO A BUILDING STRUCTURE SUCH AS A HOUSE OR DECK; NOT BE BURIED EXCEPT FOR A MAXIMUM 6" (15.2CM) IN ORDER TO CONNECT TO THE MAIN LOW VOLTAGE CABLE; AND HAVE THE LENGTH CUT OFF SO THAT IT IS CONNECTED TO A CONNECTOR WITH 6" (15.2CM) FROM A BUILDING STRUCTURE, A LUMINAIRE, OR FITTING.