



## Wi-Fi Power Supply Installation Instructions

- ① Download the “ Miboxer Smart” App and sign up new account
- ② Make sure your device is connected to your home Wi-Fi network  
(Only works on 2.4g Wi-Fi connection)
- ③ Plug in the power unit with your Wi-Fi controller
- ④ Press (+) at the top right of your app home screen

Continued on back...

- 5 The device will show up on screen saying "devices to be added", select that device. If it doesn't unplug power
- 6 Select your 2.4g Wi-Fi connection
- 7 Once the device has been added your lights will blink 3 times.
- 8 Enjoy!!!

**For additional product or installation assistance  
please call 302-294-6261.**

FOR USE WITH LANDSCAPE LIGHTING SYSTEM ONLY. THIS DEVICE IS ACCEPTED AS A LANDSCAPE LIGHTING SYSTEM WHERE THE SUITABILITY OF THE COMBINATION SHALL BE DETERMINED BY CSA OR LOCAL INSPECTION AUTHORITIES HAVING JURISDICTION. LANDSCAPE LIGHTING SYSTEMS ARE FOR OUTDOOR USE ONLY. NOT FOR USE IN DWELLING UNITS. DO NOT MOUNT POWER SUPPLY OR LUMINAIRES WITHIN 3M OF A SWIMMING POOL OR SPA. NOT FOR USE WITH SUBMERSIBLE FIXTURES. USE ONLY WITH I-LIGHTING EASY PLUG CONNECTOR CABLES AND POWER SUPPLIES. FOR ADDITIONAL CABLES PLEASE CALL 888-305-4232. THE POST LIGHTS PULL 0.7 MILLI AMPS EACH. USE ONLY 90% OF THE POWER SUPPLIES WATTAGE, ALLOWING 10% FREE. LOW VOLTAGE CABLE SHALL: BE PROTECTED BY ROUTING IN CLOSE PROXIMITY TO THE LUMINAIRE OR FITTING, OR NEXT TO A BUILDING STRUCTURE SUCH AS A HOUSE OR DECK; NOT BE BURIED EXCEPT FOR A MAXIMUM 6" (15.2CM) IN ORDER TO CONNECT TO THE MAIN LOW VOLTAGE CABLE; AND HAVE THE LENGTH CUT OFF SO THAT IT IS CONNECTED TO A CONNECTOR WITH 6" (15.2CM) FROM A BUILDING STRUCTURE, A LUMINAIRE, OR FITTING.